FEATURES & SPECIFICATIONS

PowerBlaster™ MRF100B

Model Number: MRF100B

SPECIFICATIONS	
Power	9V-300mA Power Supply (included)
IR Flasher Line Outputs	2.5mm Mono Mini Jack
RF Frequency	418 MHz
Unit Dimensions (W x H x D)	**5" x 3.25" x .75" (confirm)**
Unit Weight	**? Need Information**
Package Dimensions (W x H x D)	6.57" x 11.22" x 2.28"
Gross Unit Weight	1.608706 lbs.
Warranty	One year including parts & labor
Master Carton Quantity	12
Master Carton Dimensions (WxHxD)	14.7" x 12.4" x 15.748"
Master Carton Weight	19.3 lbs.
UPC	656787301023
	656787301023 **URC-MRF100B**
Country of Origin	Korea

PowerBlaster

> Transforms MasterControl™ Remote Controls into amazing hand-held powerhouses that send multi-directional RF (Radio Frequency) signals through walls, doors & floors -- both indoors & outdoors

HOW POWERBLASTER WORKS:

> Picks up RF signals from MasterControl Remote Controls & converts them to line-of-sight IR (Infrared) commands for your components

- > Changing the way a remote control works
- > RF (Radio Frequency) Control... means 'no more pointing!'
- > Indoors & Outdoors... picks up MasterControl remote signals through walls, doors & floors
- > Control your components from anywhere
- > Hide components behind cabinet & entertainment center doors
- > Control outdoor speakers from your patio
- > 100 Foot Range... picks up out-of-sight signals from up to 100 feet away
- > Compatibility... designed to work with MasterControl RF10, RF20 & RF30 Remote Controls

DVD Guide Included For 'Quick and Easy' Setup!

Specifications and design are subject to change without notice.

UNIVERSAL REMOTE CONTROL, INC.
500 Mamaroneck Avenue Harrison, NY 10528 Phone: (914) 835-4484 Fax: (914) 835-4532 **www.universalremote.com**